



Lamrun BT 0289 C

Chemical description

Glycols

Main use

Anti-aggregating, antistatic adjuvant for dry grinding.

Typical values

Appearance at 25 °C: Clear liquid

Density at 25 ° C: 1065 - 1110 g/l

Properties

LAMRUN BT 0289 C is a concentrated anti-aggregating, anti-static additive used in dry milling process of ceramic or cement raw materials.

LAMRUN BT 0289 C decreases the aggregation of particles, improves flowability of powders during dry milling and by consequence grinding productivity increases too, with also important benefits in terms of energy saving in the milling process.

Applications

Standard dosage of LAMRUN BT 0289 C is between 0.03 - 0.2 % on dry material, depending on kind of raw materials and equipment used for dry milling

Storage and handling

LAMRUN BT 0289 C is stable to prolonged storage under condition where extreme temperatures do not occur. The product should be stored between 5°C and 35°C and the shelf life is at least twelve months if this condition is observed.

Packaging

110 kg polyethylene drums
1100 kg tanks
1150 kg tanks

Material safety

Consult the Safety Data Sheet

ceramics.lamberti.com

Esta información y nuestras recomendaciones técnicas, de cualquier forma o ambas, verbal o escrita, se dan con el mejor de nuestros conocimientos, sin ninguna garantía expresa o implícita, por ejemplo, observando su aptitud para un uso específico. Cada usuario de nuestros productos es el único responsable de evaluar y asegurar el cumplimiento con todos los reglamentos legales incluidas las leyes de propiedad intelectual, certificaciones necesarias y autorizaciones con respecto al uso, combinación, y procesamiento de nuestros productos. Nuestras recomendaciones técnicas no liberan al usuario de la obligación de comprobar su validez y de ensayar nuestros productos para su idoneidad y aptitud para los procesos y usos previstos. La aplicación, uso y procesamiento de ambos nuestros productos y los productos fabricados por el usuario (en base a nuestras recomendaciones técnicas, de cualquier forma) están más allá de nuestro control y, por lo tanto, el usuario es el único responsable para ellos. Información detallada e instrucciones sobre el manejo de los productos y precauciones a tener en cuenta en el uso de los mismos están disponibles en nuestra Hoja de Datos de Seguridad.